

## Updating the console Version

### Updating the console system

**1** Confirm that you have the update files "SYSTEM UPDATE 2.0," on the DOS-formatted floppy disk.

**2** Connect a PS/2 keyboard (optional) to the console and turn on the power of the console. The start-up window opens.

```

DMX-R100
■■■■■
■■■■■
■■■■■
Sony Digital Audio Mixer

```

**3** Press the ESC key on the external keyboard a few times until the dialogue "Loading now....." appears in white on a blue screen.

When the console system enters the update mode of the software, the dialogue "Will you update this system? (y/n)" appears.

**4** To execute the update, press "y" on the keyboard.

If you enter this mode by mistake, press "n."  
When you press "n", the system starts as usual.

#### WARNING

Never press "y" without preparing the update floppy disks. If the DMX-R100 executes the update operations without the correct update disk, the console software files may be damaged and the console may not work properly.

When you press "y", the message "Insert the floppy disk and press any key." appears.

**5** Insert the "SYSTEM UPDATE 2.0" disk into the floppy disk drive on the console, and press the space bar on the keyboard. The specifics of the update and the "This update is ...OK? (y/n)" appear.

**6** Confirm the contents on the screen, then;

- press "y" on the keyboard, to start the update.
- if the screen shows incorrect information or parameters, press "n" to cancel the update operation.

When you press "y", the update programs are decompressed, and the disk files are installed in order, with the process showing on the screen.

When the DMX-R100 system is updated, the message "Update for XXXX completed. Remove your floppy disk and press any key..." appears.

**7** Remove the floppy disk and press the space bar on the keyboard.

**8** When the dialogue "Stand-by...." appears, turn the power of the console OFF of the console once. Wait more than 10 seconds, then turn the power ON again.

### Updating the application

After updating the DMX-R100 system, perform steps **2** to **8** again, using the "APPLICATION UPDATE 2.0" disk in step **5**.

When the update of both the system and the application are completed, the version of your DMX-R100 will be Version 2.0.